


Meter : 3-phase to zero sequence x,y



Meter : 3-phase to zero sequence x,y.....	1
1 Description	1
1.1 Pins.....	1
1.2 Parameters	1
1.3 Input.....	1
1.4 Output.....	1

1 Description

This device converts the first harmonic of the instantaneous value of 3 phase signals to the (x,y) coordinates of the corresponding zero-sequence phasor in a reference frame rotating at the fundamental frequency.

1.1 Pins

This meter has five pins:

<i>pin</i>	<i>type</i>	<i>description</i>	<i>units</i>
a	input pin	phase-a input signal	any
b	input pin	phase-b input signal	same as a
c	input pin	phase-c input signal	same as a
x	output pin	x-coordinate of zero-sequence phasor	same as a
y	output pin	y-coordinate of zero-sequence phasor	same as a

1.2 Parameters

The following parameter must be defined:

<i>parameter</i>	<i>description</i>	<i>units</i>
freq	fundamental frequency of the input signal	Hz

1.3 Input

The input pins may be connected to any control signals.
The 3 signals are the instantaneous values of a 3-phase quantity.

1.4 Output

The output is the (x,y) phasor representation of the zero-sequence transformation of the instantaneous values of the 3-phase input signals. The (x,y) coordinates are the x-axis and y-axis projections of that phasor on a reference frame rotating at the fundamental frequency.

The (x,y) coordinates of the phasor in that reference frame are calculated over a sliding time window of period equal to $1/freq$, as follows.

The (x,y) coordinates of the first harmonic of each input signal k are calculated as

$$\begin{aligned} x_k &= \frac{2}{\text{period}} \cdot \int_{t-\text{period}}^t i_{n_k}(t) \cdot \cos(2\pi \cdot \text{freq} \cdot t) \cdot dt \\ y_k &= \frac{2}{\text{period}} \cdot \int_{t-\text{period}}^t -i_{n_k}(t) \cdot \sin(2\pi \cdot \text{freq} \cdot t) \cdot dt \end{aligned} \quad (1)$$

where the negative sign for y follows the engineering convention for an inductive (lagging) current to have a negative angle when phasor rotation is counterclockwise.

The (x,y) coordinates of the zero-sequence transformation are calculated as

$$\begin{aligned} \text{seq0_x} &= \frac{1}{3} \cdot (x_a + x_b + x_c) \\ \text{seq0_y} &= \frac{1}{3} \cdot (y_a + y_b + y_c) \end{aligned} \quad (2)$$