


Flip-flop: T unclocked full-override



Flip-flop: T falling-clock full-override 1

1 Description 1

 1.1 Pins..... 1

 1.2 Parameters 1

 1.3 Input..... 2

 1.4 Output..... 2

 1.5 Representation 2

1 Description

This device is an implementation of an unclocked T flip-flop with full override controls. For a simple version without the override controls, use the device "T unclocked".

1.1 Pins

This device has seven pins:

<i>pin</i>	<i>type</i>	<i>description</i>
T	input	T input
set	input	set override
clear	input	clear override
toggle	input	toggle override
hold	input	hold override
Q	output	Q output
notQ	output	notQ output

1.2 Parameters

The initial value of Q must be defined if the device is possibly holding or toggling at $t=0$. When the device operates in clearing or setting mode at $t=0$, the initial value is ignored.

The value of the *stepped_mode* flag determines whether the device operates in *stepped* or *ramped* mode.

In *stepped* mode (the default for ideal logical signals), the outputs are represented as stepped signals, where changes in value are observed as vertical steps at the time they occur. In *ramped* mode, the value transitions of the outputs are seen as ramps between $t-\Delta t$ and t .

<i>parameter</i>	<i>description</i>
Q_ini	initial value of Q if holding or toggling at t=0
stepped_mode	=1 to indicate stepped mode (default) =0 to indicate ramped mode

1.3 Input

The input pins may be connected to any control signals.

Numerical input values are automatically interpreted as logical values by this device, as follows:

<i>input</i>	<i>converted logical value</i>	<i>logical value representation</i>
value > 0	true	1
value ≤ 0	false	0

1.4 Output

The outputs are Q and its logical inverse *not*Q. Their representation as *stepped* or *ramped* signals is determined by the value given to the parameter *stepped_mode*.

The numerical representation of the output logical values is:

<i>output logical value</i>	<i>output numerical value</i>
true	1
false	0

1.5 Representation

The implementation of the model can be inspected by opening the device's subcircuit.

The model applies the following logic for determining its state:

<i>rule sequence</i>	<i>action</i>	<i>output</i>
if set>0 else if clear>0 else if toggle>0 else if hold>0 else if T>0 else endif	setting clearing toggling holding toggling holding	Q(t) = 1 Q(t) = 0 Q(t) = not Q(t-dt) Q(t) = Q(t-dt) Q(t) = not Q(t-dt) Q(t) = Q(t-dt)
if holding at t=0 if toggling at t=0	use Q_ini use Q_ini	Q(0) = Q_ini Q(0) = Q_ini